



EQUIPMENT LAYOUT



SCHEMATIC WIRING DIAGRAM



ELECTRICAL EQUIPMENT LIST

- | | |
|--|--|
| ① Main circuit breaker – 100A, 3–pole | ⑫ Drip shield |
| ② Lighting circuit breaker – 60A, 3–pole | ⑬ Secondary neutral and ground bus according to CSA and as specified |
| ③ Traffic signal circuit breaker – 1–pole, ampacity as specified | ⑭ Primary barrier |
| ④ Circuit breaker used for relamping – 15A, 1–pole | ⑮ Secondary barrier |
| ⑤ Circuit breaker for photoelectric controller – 15A, 1–pole | ⑯ No. 3 AWG RWU90 wire or copper bus bar |
| ⑥ Lighting contactor – 60A, 3–pole, 120V coil | ⑰ No. 6 AWG RWU90 wire |
| ⑦ Branch circuit breakers – 30A, 1–pole, number of breakers as specified | ⑱ No. 12 AWG RWU90 wire |
| ⑧ Solid neutral assembly – 150A minimum, copper | ⑲ Field wiring |
| ⑨ Ground lug for No. 6 AWG stranded copper ground wire | ⑳ Copper bus bar |
| ⑩ Ground lug for No. 2/0 AWG stranded copper ground wire | ㉑ Bonding (B) conductor required for metered services |
| ⑪ Secondary lightning arrester, 650V, 3–pole | |

NOTE:

A This MTOD shall be read in conjunction with OPSD 2440.030, 2440.050, and 2440.060.

MINISTRY OF TRANSPORTATION ONTARIO DRAWING

Sep 2025

Rev 3

SUPPLY CONTROL CABINET ASSEMBLY TYPE 2

120/208V, 100A, 3–PHASE, 4–WIRE

DRAFT

MTOD 2440.020