



EQUIPMENT LAYOUT



SCHEMATIC WIRING DIAGRAM



ELECTRICAL EQUIPMENT LIST

- | | |
|--|--|
| ① Main circuit breaker – 600V, 100A, 3–pole | ⑪ Drip shield |
| ② Lighting circuit breaker – 600V, 60A, 3–pole | ⑫ Secondary neutral and ground bus according to CSA and as specified |
| ③ Circuit breaker used for relamping – 120/240V, 10A, 1–pole | ⑬ Primary barrier |
| ④ Circuit breaker for photoelectric controller – 120/240V, 10A, 1–pole | ⑭ Secondary barrier |
| ⑤ Lighting contactor – 600V, 100A, 3–pole, 120V coil | ⑮ No. 3 AWG RWU90 wire or copper bus bar |
| ⑥ Branch circuit breakers – 600/347V, 30A, 1–pole, number of breakers as specified | ⑯ No. 6 AWG RWU90 wire |
| ⑦ Solid neutral assembly – 100A minimum, copper | ⑰ No. 12 AWG RWU90 wire |
| ⑧ Ground lug for No. 6 AWG stranded copper ground wire | ⑱ Field wiring |
| ⑨ Ground lug for No. 2/0 AWG stranded copper ground wire | ⑲ Copper bus bar |
| ⑩ Secondary lightning arrester, 650V, 3–pole | ⑳ Circuit breaker for transformer, 600V, 15A |
| | ㉑ 347/120V 75VA control transformer |
| | ㉒ Bonding (B) conductor required for metered services |

NOTE:

A This MTOD shall be read in conjunction with OPSD 2440.030, 2440.050, and 2440.060.

MINISTRY OF TRANSPORTATION ONTARIO DRAWING

Sep 2025

Rev 1

SUPPLY CONTROL CABINET
ASSEMBLY TYPE 2
600/347V, 100A, 3–PHASE, 4–WIRE

DRAFT

MTOD 2440.021